



HOME [WS-E100]

Wireless Security System



WS-001 (careman)
Wireless infrared detector



WS-E10
Main Console

WS-129
Remote Control Handset

Detection & Protection



Home Care



Security Zone Setting



User can move the motion detector easily because the wireless design. Nurse aide can feel free to leave temporary because the main console can be set its reminding function in Home care, Security Zone Setting or Detection and Protection situation.



Main console can log in max. 63 sensors and add external sirens to ensure the home security. This product can be applied to Anti-burglar.Security. Elder care with optional accessories.



Before using, please log in it to main console first. Using remote control handset to main console for warning arming and disarming.



Optional Accessories

- Gas Detector
- Range Extender
- Smoke Detector
- Wireless Siren
- Door Keypad Detector(12V)
- Door/Window Detector(9v)
- Auto Dialer Alarm System
- Panic Watch Transmitter

User can equip the waterproof watch transmitter, and push the button if any necessary. The main console will sound alarm immediately which make nurse aide leave temporary and also respect user's privacy.





WS-E10 Main Console

Frequency	433.92 Mhz.
Power Source	AC120V / DC12V adaptor.
Power Consumption	7W.
Transmission	Over 50m in open space.
System Coding	Hopping Code.
Entry/Exit/Alarm	15/30/180 seconds programmable.
Low Battery Warning	When main console receives the low battery signal, it will bring Beep sound every 10 seconds.
Home Warning	When it set to home warning mode , main console will not process alarm signal from IR detector.
Back-up battery (Optional)	When the power black cut, back-up battery (9.6V/300mA) can allow it to work for 24 hours.
Dimension	105mm(H)×120mm(W)×30mm(D).
Weight	150g.

WS-129 Remote Control Handset

Power source	12V DC alkaline battery.
Buttons	Disarm, away, home, panic.
System ID	Hopping code.
Dimensions	8 × 3.8 × 1.5 cm.



WS-001 Wireless infrared detector

Color	White.
Power Source	9V alkaline battery.
IR Effective Distance	10m (appx.).
Low Battery Detection	Main console will display the low battery message (voice warning).
Detecting Sensitivity	Three levels can be selected - high / medium / low.
System Coding	Hopping code.
Dimension	155mm(H)×99mm(W)×72mm(D).
Weight	205g.



WS-129
Remote Control Handset



WS-E10
Main Console



WS-001 (careman)
Wireless infrared detector